



PORTABLE GASOLINE GENSET

Continuous Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a constant electrical load. Average load can be 100%. The generator must not be overloaded.

Standby Power

The maxpower available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 hrs of operation per year under average of 70%load.Overloading isn't permissible.

Prime Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hrs.

Genset

Standby	kVA	12
Prime	kVA	11
Start System		Electric Start
Power Factor	CosΦ	1.0
Voltage		220(50HZ)
Fuel Type		Gasoline
Fuel Tank Capacity	lt	50

Engine

Model		2V80
Kw (Standby/Prime)		11 / 10
Bore / Stroke	mm	80 x 72
Number of Cylinder / Type		2 / V Type
Displacement	cc	723
Oil Capacity	lt	1,6
Engine Type		4-Stroke, Air Cooled,OHV

Size

Weight	kg	151
L x W x H	cm	81x 67 x 82