



## PORTABLE GASOLINE GENSET

### Continuous Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a constant electrical load. Average load can be 100%. The generator must not be overloaded.

### Standby Power

The maxpower available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 hrs of operation per year under average of 70%load.Overloading isn't permissible.

### Prime Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hrs.

### Genset

Standby	kVA	9,5
Prime	kVA	8,6
Start System		Electric Start
Power Factor	CosΦ	1.0
Voltage		380(50HZ)
Fuel Type		Gasoline
Fuel Tank Capacity	lt	25

### Engine

Model		192F
Kw (Standby/Prime)		7,5 / 7
Bore / Stroke	mm	92 x 69
Number of Cylinder		1
Displacement	cc	460
Oil Capacity	lt	1,1
Engine Type		4-Stroke, Air Cooled,OHV

### Size

Weight	kg	98
L x W x H	cm	70 x 59 x 56